



AGM JUMP STARTER

PBI 2400HD ⚡ 12/24V 🔌 2400/1200 CA



+++

Rotomolded and unbreakable housing

Retractable handle & puncture-proof wheels

12V accessory outlet
also used for memory saver mode

Anderson connectors for voltage
selection (12/24V)

Heavy-duty curved clamps & double-insulated,
ultra-flexible 50mm² cable

Reverse polarity buzzer

Optional: Auxiliary connector for auxiliary
cables

500A fuse for short-circuit protection and
1 spare fuse



SLOVENSKI ZASTOPNIK



soncna.uprava@telemach.net

THE PBI RANGE



PBI 1812

PBI 200

PBI 201

PBI 2400 HD

TECHNICAL INFORMATION

MODEL	PBI 1812	PBI 200	PBI 201	PBI 2400 HD
PART NUMBER	94065001C	94065200C	94065201C	232008
VOLTAGE (DC)	12V	12V	12/24V	12/24V
CRANKING AMPS (CA)	700	900	1800/900	2400/1200
CABLE LENGTH	0,71 m	1,59 m	1,70 m	1,52 m
CABLE CROSS SECTION	21 mm ²	21 mm ²	33 mm ²	50 mm ²
AUTOMATIC CHARGER	0,7 A	2 A	2 A	4 A



PACKAGING INFORMATION

MODEL	PBI 1812	PBI 200	PBI 201	PBI 2400 HD
NET WEIGHT	9,25 kg	11,75 kg	20,8 kg	30,5 kg
DIMENSIONS (L x W x H / mm)	330 x 170 x 363	360 x 150 x 440	425 x 230 x 455	475 x 290 x 550

HOW TO CHOOSE

HOW TO CHOOSE			12V							24V					
PART NUMBER	MODEL	VOLTAGE	<125*	150	175	250	300	350	500	100	250	500	1000	1500	2000
			HP* = CHECK YOUR ENGINE HP - LEGEND: ■ NORMAL ■ INTENSIVE												
94065001C	PBI 1812	12V	■ ■	■	■										
94065200C	PBI 200	12V	■ ■	■ ■	■	■									
94065201C	PBI 201	12/24V	■ ■	■ ■	■ ■	■	■	■		■ ■	■ ■	■			
232008	PBI 2400 HD	12/24V	■ ■	■ ■	■ ■	■ ■	■ ■	■ ■	■	■ ■	■ ■	■ ■	■	■	

RELATED BATTERY CHARGER PART NUMBER:

PBI 1812

EU: 94065021
UK: 94065022

PBI 200

EU: 2299003058CZ
UK: 2299003058GZ

PBI 201

EU: 2299003058CZ
UK: 2299003058GZ

PBI 2400 HD

EU: 865124-A
UK: 865124-A + 976158



SLOVENSKI ZASTOPNIK



soncna.uprava@telemach.net

Since
1947

#passionatesince1947